


P33-3

Output Ratings					
Voltage, Frequenc	у	Prime	Standby		
400/230V, 50 Hz	kVA	30	33		
	kW	24	26.4		
480/277V, 60 Hz	kVA	33.8	37.5		
	kW	27	30		



Please refer to the output ratings technical data section for specific generator set outputs per voltage.



		1			
					197
1			-		
				10.	
	A	É			N.
		C		-	

Soundproof Dimensions					
Length	cm	194.7			
Width	cm	86.5			
Height	cm	124			

Ratings in accordance with ISO 8528, ISO 3046, IEC 60034, BS5000 and NEMA MG-1.22. Generator set pictured may include optional accessories.

Prime Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

Standard Reference Conditions

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m (328 ft) A.S.L. 30% relative humidity. Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998, Class A2.

FG Wilson offer a range of optional features to allow you to tailor our generator sets to meet your power needs. Options available include:

- Upgrade to CE Certification
- A wide range of Sound Attenuated Enclosures
- A variety of generator set control and synchronising panels
- · Additional alarms and shutdowns
- A selection of exhaust silencer noise levels

For further information on all of the standard and optional features accompanying this product please contact your local Dealer or visit:

www.fgwilson.com



Ratings and Perform	ance Data		
Engine Make		Perkins	
Engine Model:		1103A-33G1	
Alternator Make		Marelli	
Alternator Model:		MJB 160 MB4	
Base Frame:		Heavy Duty Fabricated Ste	eel
Circuit Breaker Type:		3 Pole MCB	
Frequency:		50 HZ	60 HZ
Engine Speed: RPM	rpm	1500	1800
Fuel Tank Capacity:	litres	54	
Fuel Consumption Prime	litres (US gal)	6.9 (1.8)	8.1 (2.1)
Fuel Consumption Standby	litres (US gal)	7.7 (2.0)	9.1 (2.4)
Engine Technical Da	ta		
No. of Cylinders		3	
Alignment		In Line	
Cycle		4 Stroke	
Bore m	m (in)	105.0 (4.1)	
Stroke m	m (in)	127.0 (5.0)	
Induction		Naturally Aspirated	
Cooling Method		Water	
Governing Type		Mechanical	
Governing Class		ISO 8528 G2	
Compression Ratio		19.25:1	
Displacement L ((cu. in)	3.3 (201.4)	
Moment of Inertia: kg	j m² (lb/in²)	1.14 (3896)	
Voltage		12	
Ground		Negative	
Battery Charger Amps		65	
Engine Weight Dry kg	ı (lb)	412 (908)	
Engine Weight Wet kg	ı (lb)	430 (948)	
Engine Performance	e Data	50 Hz	60 Hz
Engine Speed	rpm	1500	1800
Gross Engine Power Prime	kW (hp)	28.2 (38.0)	33.1 (44.0)
Gross Engine Power Standby	kW (hp)	31.0 (42.0)	36.5 (49.0)
BMEP Prime	kPa (psi)	684.0 (99.2)	669.0 (97.0)
BMEP Standby	kPa (psi)	752.0 (109.0)	738.0 (107.0)



0.5 (0.7)

84.8 (2995)

125 (0.5)

Fuel System					
Fuel Filter Type:			Replaceable Eler	ment	
Recommended Fuel:			Class A2 Diesel		
Fuel Consumption at		110 % Load	100 % Load	75 % Load	50 % Load
50 Hz Prime:	l/hr (US gal/hr)	7.7 (2.0)	6.9 (1.8)	5.2 (1.4)	3.8 (1.0)
50 Hz Standby	l/hr (US gal/hr)	-	7.7 (2.0)	5.7 (1.5)	4.1 (1.1)
60 Hz Prime	I/hr (US gal/hr)	9.1 (2.4)	8.1 (2.1)	6.2 (1.6)	4.7 (1.2)
60 Hz Standby	I/br (LIS gal/br)	<u>-</u>	91 (24)	68 (18)	5.0 (1.3)

(Based on diesel fuel with a specific gravity of 0.84 and conforming to BS2869 classA2,EN590 $\,$

Air System		50 Hz	60 Hz
Air Filter Type:			Replaceable Element
Combustion Air Flow Prime	m³/min (cfm)	2.2 (76)	2.6 (92)
Combustion Air Flow Standby	m³/min (cfm)	2.2 (76)	2.6 (91)
Max. Combustion Air Intake Restriction	kPa	6.5 (26.1)	6.5 (26.1)
Cooling System		50 Hz	60 Hz
Cooling System Capacity	l (US gal)	10.2 (2.7)	10.2 (2.7)
Water Pump Type:			Centrifugal
Heat Rejected to Water & Lube Oil: Prime	kW (Btu/min)	16.0 (910)	18.0 (1024)
Heat Rejected to Water & Lube Oil: Standby	kW (Btu/min)	18.0 (1024)	22.0 (1251)
Heat Radiation to Room*: Prime	kW (Btu/min)	8.1 (461)	8.8 (500)
Heat Radiation to Room*: Standby	kW (Btu/min)	9.8 (557)	10.4 (591)

0.3 (0.4)

125 (0.5)

62.6 (2211)

Radiator Fan Load:

Radiator Cooling Airflow:

Designed to operate in ambient conditions up to 50°C (122°F).

Contact your local FG Wilson Dealer for power ratings at specific site conditions.

kW (hp)

m³/min (cfm)

Pa (in H2O)

Lubrication Sys	Lubrication System		
Oil Filter Type:		Spin-On, Full Flow	
Total Oil Capacity:	I (US gal)	8.3 (2.2)	
Oil Pan Capacity:	l (US gal)	7.8 (2.1)	
Oil Type:		API CG4 / CH4 15W-40	
Oil Cooling Method:		Water	

Exhaust System		50 Hz	60 Hz
Maximum Allowable Back Pressure:	kPa (in Hg)	8.0 (2.4)	10.0 (3.0)
Exhaust Gas Flow: Prime	m³/min (cfm)	5.7 (201)	6.4 (226)
Exhaust Gas Flow: Standby	m³/min (cfm)	5.8 (205)	6.6 (233)
Exhaust Gas Temperature: Prime	°C (°F)	500 (932)	520 (968)
Exhaust Gas Temperature: Standby	°C (°F)	520 (968)	530 (986)

External Restriction to Cooling Airflow: *: Heat radiated from engine and alternator



Alternator Physical	Data						
No. of Bearings:					1		
Insulation Class:					Н		
Winding Pitch:					2/3		
Winding Code				MO			
Wires:				12			
Ingress Protection Rating:					IP23		
Excitation System:				:	SHUNT		
AVR Model:					Mark V		
dependant on voltage code selected	d						
Alternator Operatin	ng Data						
Overspeed: rpm					2250		
Voltage Regulation: (Steady	state)	%			+/- 1.0%		
Wave Form NEMA = TIF:					50		
Wave Form IEC = THF:		%			2.0%		
Total Harmonic content LL/l	_N:	%			2.0%		
Radio Interference:					EN 55011		
Radiant Heat: 50 Hz		kW (Btu/min) 3.8 (216)					
naulatit i leat. 30 i iz		KVV (DEG/11111)			()		
Radiant Heat: 60 Hz	ance Da	kW (Btu/min)			4.4 (250)		
	ance Da	kW (Btu/min)	415/240V	400/230V 230/115V		220/127V	
Alternator Performa Voltage Code		kW (Btu/min)		400/230V 230/115V 200/115V	380/220V 220/110V		
Alternator Performa Voltage Code Motor Starting Capability*	kVA	kW (Btu/min)	45	400/230V 230/115V 200/115V 45	380/220V 220/110V 38	58	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA %	kW (Btu/min)	45 300	400/230V 230/115V 200/115V 45 300	380/220V 220/110V 38 300	58 300	
Alternator Performa Voltage Code Motor Starting Capability*	kVA % Xd	kW (Btu/min)	45 300 2.390	400/230V 230/115V 200/115V 45 300 2.570	380/220V 220/110V 38 300 2.840	58 300 2.120	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA %	kW (Btu/min)	45 300	400/230V 230/115V 200/115V 45 300	380/220V 220/110V 38 300	58 300	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances	kVA % Xd X'd X"d	kW (Btu/min)	45 300 2.390 0.220	400/230V 230/115V 200/115V 45 300 2.570 0.230	380/220V 220/110V 38 300 2.840 0.260	58 300 2.120 0.190	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd X'd X"d	kW (Btu/min) ata 50 Hz:	45 300 2.390 0.220 0.100	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260	58 300 2.120 0.190 0.083	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation	kVA % Xd X'd X"d	ata 50 Hz: ata 60 Hz 480/277V	45 300 2.390 0.220 0.100	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260	58 300 2.120 0.190 0.083	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation	kVA % Xd X'd X"d	kW (Btu/min) ata 50 Hz:	45 300 2.390 0.220 0.100	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260	58 300 2.120 0.190 0.083	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances	kVA % Xd X'd X"d	ata 50 Hz: ata 60 Hz 480/277V	45 300 2.390 0.220 0.100	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260	58 300 2.120 0.190 0.083	
Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa Voltage Code	kVA % Xd X'd X"d	ata 50 Hz: ata 60 Hz 480/277V 240/139V	45 300 2.390 0.220 0.100 380/220V 220/110V	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260 0.111	58 300 2.120 0.190 0.083 440/254V 220/127V	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation Voltage Code Motor Starting Capability*	kVA % X'd X'd X"d	ata 50 Hz: ata 60 Hz 480/277V 240/139V	45 300 2.390 0.220 0.100 380/220V 220/110V	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100	380/220V 220/110V 38 300 2.840 0.260 0.111	58 300 2.120 0.190 0.083 440/254V 220/127V	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd X'd X"d Ance Da	ata 50 Hz: ata 60 Hz 480/277V 240/139V 39 300	380/220V 220/110V	400/230V 230/115V 200/115V 45 300 2.570 0.230 0.100 240/120V 208/120V	380/220V 220/110V 38 300 2.840 0.260 0.111	58 300 2.120 0.190 0.083 440/254V 220/127V 39 300	

Reactances shown are applicable to prime ratings.

^{*}Based on 30% voltage dip at 0 power factor.

^{**} With optional independant excitation system (PMG / AUX winding)



Output Ratings	50 Hz			
		Prime		Standby
Voltage Code	kVA	kW	kVA	kW
415/240V	30	24	33	26.4
400/230V	30	24	33	26.4
380/220V	30	24	33	26.4
230/115V	30	24	33	26.4
220/127V	30	24	33	26.4
220/110V	30	24	33	26.4
200/115V	30	24	33	26.4
240V	-	-	-	-
230V	-	-	-	-
220V	-	-	-	-
Output Ratings	60 Hz			
		Prime		Standby
Voltage Code	kVA	kW	kVA	kW
480/277V	33.8	27	37.5	30
440/254V	33.8	27	37.5	30
416/240V	-	-	-	-
400/230V	-	-	-	-
380/220V	31.8	25.4	35	28
240/139V	33.8	27	37.5	30
240/120V	33.8	27	37.2	29.8
230/115V	_			

27

25.4

27

37.5

35

37.2

30

28

29.8

33.8

31.8

33.8

220/127V 220/110V

208/120V

240/120 220/110





P33-3

Dealer Contact Details



Documentation

Operation and maintenance manual including circuit wiring diagrams.

Generator Set Standards

The equipment meets the following standards: BS5000, ISO 8528, ISO 3046, IEC 60034, NEMA MG-1.22.

Warranty

6.8 – 750 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760). For standby applications the warranty period is 24 months from date of start-up, limited to 500 hours per year.

730 – 2500 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760 hours) or 24 months from date of start-up, limited to 6000 hours. For standby applications the warranty period is 36 months from date of start-up, limited to 500 hours per year.

FG Wilson manufactures product in the following locations:

Northern Ireland • Brazil • China • India

With headquarters in Northern Ireland, FG Wilson operates through a Global Dealer Network. To contact your local Sales Office please visit the FG Wilson website at www.fgwilson.com.

FG Wilson is a trading name of Caterpillar (NI) Limited.